DKG-519 MANUAL & REMOTE START UNIT CANBUS AND MPU VERSIONS

STATUS ALABAN ASSOCIATION WARRING! T TEST RUN DKG 519 LANGE STATUS ALABAN ASSOCIATION OF THE STATUS AUTO AUTO STATUS ALABAN ASSOCIATION OF THE STATUS AUTO STOP

DESCRIPTION

The DKG-519 is a comprehensive generator control unit designed to start and stop the generating set both manually and remotely. The manual control is made using the pushbuttons on the front panel. The remote control is made via the **REMOTE START** input signal.

The unit is available with MPU or CANBUS versions. The CANBUS version connects to ECU controlled electronic engines providing engine control, protection and instrumentation without extra senders. The ECU alarms are displayed in text.

The unit has an optional internal GSM modem module and is able to initiate modem calls and send SMS messages in fault conditions through either internal or external modems.

The unit provides a comprehensive set of digitally adjustable timers, threshold levels, input and output configurations, operating sequences and engine types. All programs may be modified via front panel pushbuttons, and do not require an external unit.

Last 100 faults are stored in the event log file. The event log includes not only the date-time information, but also a comprehensive list of measured genset parameters at the time that the fault has occurred.

The WINDOWS based RAINBOW program allows remote monitoring and control.

The unit supports MODBUS protocol enabling communication with PLCs and building management systems. The MODBUS protocol is also supported through GSM and PSTN modems.

The unit offers multiple language support.

MEASUREMENTS

Generator Volts: L1-N, L2-N, L3-N Generator Volts: L1-L2, L2-L3, L3-L1

Generator Amps: L1, L2, L3 Generator KW: L1, L2, L3, total Generator pf: L1, L2, L3, total

Generator Frequency

Engine rpm Battery Voltage

Engine Coolant Temperature

Engine Oil Pressure

Fuel Level

Engine Oil Temperature

FEATURES

True RMS measurements
ECU connection through J1939 CAN option
J1939 ECU warnings displayed as text
MPU input option

Internal GSM modem option

Dual genset mutual standby operation

Event logging with time stamp and

measurements

Battery backed-up real time clock
Built in daily / weekly / monthly exerciser
Weekly operation schedule programs
Field adjustable parameters
RS-232 serial port

Optional RS-485 serial port
Free MS-Windows Remote monitoring SW
GSM and PSTN modem support
GSM SMS message sending on fault
MODBUS communications
Multiple language support

Customer logo display capability 10ADC relay outputs

Configurable analogue inputs: 4
Configurable digital inputs: 7
Configurable relay outputs: 2
Total relay outputs: 4

Total relay outputs: 4

I/O expansion capability

Plug-in connection system











DIGITAL INPUTS

The unit has 7 configurable digital inputs. Each input is fully configurable with selectable names, alarm type, polling, latching and contact type.

ANALOG INPUTS

Engine analog inputs are provided for coolant temperature, oil pressure, oil temperature and fuel level. The inputs have programmable sensor characteristics so that they are suitable for any type and brand of sensors.

RELAY OUTPUTS

The unit provides 4 relay outputs and 2 of them have programmable functions, selectable from a list. Any function or alarm condition may be output as a relay output. Using two Relay Expansion Modules, the number of relays may be increased to 20, 16 of them being volt-free contacts.

EVENT LOGGING

The unit records last 100 events with date-time stamp and a total of 18 measured parameters.

TELEMETRY AND REMOTE PROGRAMMING

The unit provides the user with large telemetry facilities via its standard RS-232 serial port, connecting either to a PC, PLC or a GSM or PSTN modem. It supports both RAINBOW and MODBUS communication protocols. The standard PC software offers local and modem operation capabilities as well as modem networking feature.

The PC program is used for below purposes:

- -parameter upload/download
- -remote monitoring and control
- -diagnostics and analysis

The MODBUS interface allows the unit to be integrated in building management systems.

TECHNICAL SPECIFICATIONS

Alternator voltage: 0 to 300 V-AC (Ph-N) Alternator frequency: 0-100 Hz. DC Supply Range: 9.0 to 33.0 V-DC Cranking dropouts: survives 0 V for 100ms. Typical Standby Current: 100 mA-DC

Maximum Operating Current: 200 mA-DC (Relay outputs open)

DC Outputs: 10A @ 28V Charge excitation: min 2 Watts Magnetic pickup input:: 0.5 – 30 V-AC. Magnetic pickup frequency: 10 KHz max.

Current inputs: from CTs, .../5A. Max load 0.7VA per phase.

Analog input range: 0-5000 ohms.

Serial port: RS-232, 9600 bauds, no parity, 1 bit stop Operating temp.: -20°C (-4°F) to 70 °C (158°F). Storage temp.: -40°C (-40°F) to 80 °C (176°F). Maximum humidity: 95% non-condensing. Dimensions: 200 x 148 x 46 mm (WXHXD)

Panel Cut-out Dimensions: 176x121 mm minimum.

Weight: 420 g (approx.)

Case Material: High Temperature ABS/PC (UL94-V0)

IP Protection: IP65 from front panel, IP30 from the rear

Installation: Flat surface mounting on a Type 1 Enclosure. Rear

retaining plastic brackets.

CE Conformity reference standards:

EN 61010 (safety requirements) EN 61326 (EMC requirements)

UL / CSA Conformity: certificate # 20110527-E314374

UL 508, Edition 17 UL 2200, 1st Edition. UL 840 Edition 3

CSA C22.2 NO. 14 - Edition 10



